

# NERC

NORTH AMERICAN ELECTRIC  
RELIABILITY CORPORATION

# Appendix 5B

## Statement of Compliance Registry Criteria Revision 8

### Effective: June 27, 2024

**RELIABILITY | RESILIENCE | SECURITY**



**3353 Peachtree Road NE  
Suite 600, North Tower  
Atlanta, GA 30326  
404-446-2560 | [www.nerc.com](http://www.nerc.com)**

# Table of Contents

---

Statement of Compliance Registry Criteria (Revision 8) ..... 1

    Summary..... 1

    Background..... 2

    Statement of Issue ..... 2

    Resolution..... 2

    Registry Criteria ..... 2

    Determination of Material Impact ..... 6

    Limitation of responsibilities to a sub-set of Reliability Standards ..... 6

# Statement of Compliance Registry Criteria (Revision 8)

---

## Summary

This document describes how the North American Electric Reliability Corporation (NERC) will identify organizations that may be candidates for Registration and assign them to the Compliance Registry.

NERC and the Regional Entities<sup>1</sup> have the obligation to identify and register all entities that meet the criteria for inclusion in the Compliance Registry, as further explained in the balance of this document.

Organizations will be responsible to register and to comply with approved Reliability Standards to the extent that they are owners, operators, and users of the Bulk Power System (BPS), perform a function listed in the functional types identified in Section II of this document, and are material to the Reliable Operation of the interconnected BPS as defined by the criteria and sections set forth in this document. NERC will apply the following principles to the Compliance Registry:

- In order to carry out its responsibilities related to enforcement of Reliability Standards, NERC must identify the owners, operators, and users of the BPS who have a material impact<sup>2</sup> on the BPS through a Compliance Registry. NERC and the Regional Entities will make their best efforts to identify all owners, users and operators who have a material impact on the BPS in order to develop a complete and current Compliance Registry list. The Compliance Registry will be updated as required and maintained on an on-going basis.
- Organizations listed in the Compliance Registry are responsible and will be monitored for compliance with applicable mandatory Reliability Standards. They will be subject to NERC's and the Regional Entities' Compliance Monitoring and Enforcement Programs.
- NERC and Regional Entities will not monitor nor hold those not in the Compliance Registry responsible for compliance with the Reliability Standards. An entity which is not initially placed on the Compliance Registry, but which is identified subsequently as having a material impact on the BPS, will be added to the Compliance Registry. Such entity will not be subject to a sanction or Penalty by NERC or the Regional Entity for actions or inactions prior to being placed on the Compliance Registry, but may be required to comply with a Remedial Action Directive or Mitigation Plan in order to become compliant with applicable Reliability Standards. After such entity has been placed on the Compliance Registry, it shall be responsible for complying with Reliability Standards and may be subject to sanctions or Penalties as well as any Remedial Action Directives and Mitigation Plans required by the Regional Entities or NERC for future violations, including any failure to follow a Remedial Action Directive or Mitigation Plan to become compliant with Reliability Standards.
- Required compliance by a given organization with the Reliability Standards will begin the later of (i) inclusion of that organization in the Compliance Registry and (ii) approval by the Applicable Governmental Authority of mandatory Reliability Standards applicable to the registered entity.

Entities responsible for funding NERC and the Regional Entities have been identified in the budget documents filed with FERC.<sup>3</sup> Presence on or absence from the Compliance Registry has no bearing on an entity's independent responsibility for funding NERC and the Regional Entities.

---

<sup>1</sup> The term "Regional Entities" includes Cross-Border Regional Entities that have footprints in the U.S., Canada, and Mexico, as applicable. Applicable Governmental Authorities in Canadian jurisdictions may have adopted their own Rules of Procedure and Compliance Registry requirements. Registered Entities may be subject to the Compliance Monitoring and Enforcement Programs (CMEP) in their respective jurisdictions, in accordance with applicable laws and regulations.

<sup>2</sup> The criteria for determining whether an entity will be placed on the Compliance Registry are set forth in the balance of this document. At any time a person may recommend in writing, with supporting reasons, to the Director of Compliance (or an equivalent position) that an organization be added to or removed from the Compliance Registry, pursuant to NERC Rules of Procedure Section 501.1.3.5.

<sup>3</sup> Budget documents are submitted to Applicable Governmental Authorities in Canada for information.

## Background

The initial Registration process began in January of 2006. Registration of new entities is an ongoing process. If a Registered Entity's information changes, these changes must be submitted to the applicable Regional Entity(ies). Based on selection as the ERO, NERC's Organization Registration program<sup>4</sup> is the means by which NERC and the Regional Entities plan, manage, and execute Reliability Standard compliance oversight of owners, operators, and users of the BPS. Organizations listed in the Compliance Registry are subject to NERC's and the Regional Entities' Compliance Monitoring and Enforcement Programs.

## Statement of Issue

As the ERO, NERC intends to comprehensively and thoroughly protect the reliability of the grid. To support this goal NERC will include in its Compliance Registry each entity that NERC concludes can materially impact the reliability of the BPS.

NERC will identify those entities that may need to be listed in its Compliance Registry. Identifying these organizations is necessary and prudent for the purpose of determining resource needs, both at the NERC and Regional Entity level, and for communicating with these entities regarding their potential responsibilities and obligations. Candidate entities can be identified at any time, as and when needed. The Compliance Registry is available on NERC's website.

## Resolution

The potential costs and effort of registering every organization potentially within the scope of "owner, operator, and user of the BPS," while ignoring their impact upon reliability, would be disproportionate to the improvement in reliability that would reasonably be anticipated from doing so.

NERC and the Regional Entities have identified two principles they believe are key to the entity selection process. These are:

1. There needs to be consistency between Regions and across the continent with respect to which entities are registered; and
2. Any entity reasonably deemed material to the reliability of the BPS will be registered, irrespective of other considerations.

To address the second principle the Regional Entities, working with NERC, will identify and register any entity they deem material to the reliability of the BPS.

## Registry Criteria

In order to promote consistency, NERC and the Regional Entities use the following criteria as the basis for determining whether particular entities should be identified as candidates for Registration. All organizations meeting or exceeding the criteria will be identified as candidates.

The following criteria (Sections I-V) plus the statement in Section VI will provide guidance regarding an entity's Registration status:

- I. Owners, operators, or users of the BPS are candidates for Registration.<sup>5</sup>

---

<sup>4</sup> See NERC ERO Application; Exhibit C; Section 500 – Organization Registration and Certification.

<sup>5</sup> See NERC Rules of Procedure Section 501.1 NERC Compliance Registry — NERC shall establish and maintain the NCR of the BPS owners, operators, and users that are subject to approved Reliability Standards. For purposes of this Section I, users, owners, and operators of the BPS includes: 1) entities that use, own, or operate Elements of the Bulk Electric System (BES) as defined in Appendix 2 of the NERC Rules of Procedure and NERC Glossary of Terms; as well as 2) entities otherwise defined in the Registry Criteria in this Appendix 5B.

## Statement of Compliance Registry Criteria (Revision 8)

- II. Entities identified in Section I above will be categorized as Registration candidates who may be subject to Registration under one or more appropriate Functional Entity types based on a comparison of the functions the entity normally performs against the following function type definitions.<sup>6</sup>

Function Type	Acronym	Definition/Discussion
Balancing Authority	BA	The responsible entity that integrates resource plans ahead of time, maintains Load-interchange-generation balance within a Balancing Authority Area, and supports Interconnection frequency in real-time.
Distribution Provider	DP	Provides and operates the “wires” between the transmission system and the end-use customer. For those end-use customers who are served at transmission voltages, the Transmission Owner also serves as the Distribution Provider. Thus, the Distribution Provider is not defined by a specific voltage, but rather as performing the distribution function at any voltage.  Note: As provided in Section III.b.1 below, a Distribution Provider entity shall be an Underfrequency Load Shedding (UFLS)-Only Distribution Provider if it is the responsible entity that owns, controls or operates UFLS Protection System(s) needed to implement a required UFLS program designed for the protection of the BES, but does not meet any of the other registration criteria for a Distribution Provider.
Frequency Response Sharing Group	FRSG	A group whose members consist of two or more Balancing Authorities that collectively maintain, allocate, and supply operating resources required to jointly meet the sum of the Frequency Response Obligations of its members.
Generator Operator	GOP	The entity that: 1) operates generating Facility(ies) and performs the functions of supplying energy and Interconnected Operations Services (Category 1 GOP); or 2) operates non-BES inverter based generating resources that either have or contribute to an aggregate nameplate capacity of greater than or equal to 20 MVA, connected through a system designed primarily for delivering such capacity to a common point of connection at a voltage greater than or equal to 60 kV (Category 2 GOP).
Generator Owner	GO	The entity that: 1) owns and maintains generating Facility(ies) (Category 1 GO); or 2) owns and maintains non-BES inverter based generating resources that either have or contribute to an aggregate nameplate capacity of greater than or equal to 20 MVA, connected through a system designed primarily for delivering such capacity to a common point of connection at a voltage greater than or equal to 60 kV (Category 2 GO).

<sup>6</sup> Exclusion: An entity will not be registered based on these criteria if responsibilities for compliance with approved NERC Reliability Standards or associated Requirements including reporting have been transferred by written agreement to another entity that has registered for the appropriate function for the transferred responsibilities, including bilateral agreements and Sections 501, 507, and 508 of the NERC Rules of Procedure.

## Statement of Compliance Registry Criteria (Revision 8)

Function Type	Acronym	Definition/Discussion
Planning Authority/ Planning Coordinator	PA/PC	The responsible entity that coordinates and integrates transmission Facilities and service plans, resource plans, and Protection Systems.
Reliability Coordinator	RC	The entity that is the highest level of authority who is responsible for the Reliable Operation of the BES, has the Wide Area view of the BES, and has the operating tools, processes and procedures, including the authority to prevent or mitigate emergency operating situations in both next-day analysis and real-time operations. The Reliability Coordinator has the purview that is broad enough to enable the calculation of Interconnection Reliability Operating Limits, which may be based on the operating parameters of transmission systems beyond any Transmission Operator's vision.
Regulation Reserve Sharing Group	RRSG	A group whose members consist of two or more Balancing Authorities that collectively maintain, allocate, and supply the Regulating Reserve required for all member Balancing Authorities to use in meeting applicable regulating standards.
Reserve Sharing Group	RSG	A group whose members consist of two or more Balancing Authorities that collectively maintain, allocate, and supply Operating Reserves required for each Balancing Authority's use in recovering from contingencies within the group. Scheduling energy from an Adjacent Balancing Authority to aid recovery need not constitute reserve sharing provided the transaction is ramped in over a period the supplying party could reasonably be expected to load generation in (e.g., ten minutes). If the transaction is ramped in more quickly (e.g., between zero and ten minutes), then, for the purposes of recovery from a Reportable Balancing Contingency Event, the areas become a Reserve Sharing Group.
Resource Planner	RP	The entity that develops a long-term (generally one year and beyond) plan for the resource adequacy of specific Loads (customer demand and energy requirements) within a Planning Authority area.
Transmission Owner	TO	The entity that owns and maintains transmission Facilities.
Transmission Operator	TOP	The entity responsible for the reliability of its local transmission system and operates or directs the operations of the transmission Facilities.
Transmission Planner	TP	The entity that develops a long-term (generally one year and beyond) plan for the reliability (adequacy) of the interconnected bulk electric transmission systems within its portion of the Planning Authority area.
Transmission Service Provider	TSP	The entity that administers the transmission tariff and provides Transmission Service to Transmission Customers under applicable Transmission Service agreements.

---

Statement of Compliance Registry Criteria (Revision 8)

---

III. Entities identified in Section II above as being subject to Registration as a Distribution Provider should be included in the Compliance Registry for these functions only if they meet any of the criteria listed below:

III(a) Distribution Provider:

- III.a.1 Distribution Provider system serving >75 MW of peak Load that is directly connected to the BES;<sup>7</sup> or
- III.a.2 Distribution Provider is the responsible entity that owns, controls, or operates Facilities that are part of any of the following Protection Systems or programs designed, installed, and operated for the protection of the BES:<sup>8</sup>
  - a required Undervoltage Load Shedding (UVLS) program and/or
  - a required Special Protection System or Remedial Action Scheme and/or
  - a required transmission Protection System; or
- III.a.3 Distribution Provider that is responsible for providing services related to Nuclear Plant Interface Requirements (NPIRs) pursuant to an executed agreement; or
- III.a.4 Distribution Provider with field switching personnel identified as performing unique tasks associated with the Transmission Operator's restoration plan that are outside of their normal tasks.

III(b) Distribution Provider with UFLS-Only assets (referred to as "UFLS-Only Distribution Provider")

- III.b.1 UFLS-Only Distribution Provider does not meet any of the other registration criteria in Sections III(a)(1)-(4) for a Distribution Provider; and
- III.b.2 UFLS-Only Distribution Provider is the responsible entity that owns, controls, or operates UFLS Protection System(s) needed to implement a required UFLS Program designed for the protection of the BES.

*The Reliability Standards applicable to UFLS-Only Distribution Providers are: (1) any version of PRC-005 and PRC-006 applicable to UFLS-Only Distribution Providers, (2) any regional Reliability Standard whose purpose is to develop or establish a UFLS Program, and (3) any Reliability Standard that lists UFLS-Only Distribution Provider in the applicability section. Reliability Standards that apply to Distribution Providers will not apply to UFLS-Only Distribution Providers, unless explicitly stated in the applicability section of these Reliability Standards and in future revisions and/or versions.*

IV. Joint Registration Organization, Coordinated Functional Registration and applicable Member Registration.

Pursuant to FERC's directive in paragraph 107 of Order No. 693, NERC's rules pertaining to joint Registrations and Joint Registration Organizations, as well as Coordinated Functional Registrations, are now found in Section 501, 507, and 508 of the NERC Rules of Procedure.

V. If NERC or a Regional Entity encounters an organization that is not listed in the Compliance Registry, but which should be subject to the Reliability Standards, NERC or the Regional Entity is obligated and will initiate actions to add that organization to the Compliance Registry, subject to that organization's right to challenge as provided in Section 500 of NERC's Rules of Procedure.

---

<sup>7</sup> Ownership, control or operation of UFLS Protection System(s) needed to implement a required UFLS Program designed for the protection of the BES does not affect an entity's eligibility for registration pursuant to III.a.1.

<sup>8</sup> As used in Section III.a.2, "protection of the Bulk Electric System" means protection to prevent instability, Cascading, or uncontrolled separation of the BES and not for local voltage issues (UVLS) or local line loading management (Special Protection System) that are demonstrated to be contained within a local area.

---



## Determination of Material Impact<sup>9</sup>

An entity that does not meet (i.e., falls below) the criteria may nevertheless be registered if it can be demonstrated that the entity has a material impact on the reliability of the BPS. Similarly, an entity that meets the criteria may be excluded if it can be demonstrated to NERC that the entity does not have a material impact on the reliability of the BPS. Such Registration decisions regarding materiality must be made by the NERC-led Registration Review Panel in accordance with Section III(D) of Appendix 5A to the NERC Rules of Procedure. In order to ensure a consistent approach to assessing materiality, a non-exclusive set of factors (“materiality test”) for consideration is identified below; however, only a sub-set of these factors, or other additional factors, may be applicable to a particular functional registration category or specific entity, as appropriate:

1. Is the entity specifically identified in the emergency operation plans and/or restoration plans of an associated Reliability Coordinator, Balancing Authority, Generator Operator or Transmission Operator?
2. Will intentional or inadvertent removal of an Element owned or operated by the entity, or a common mode failure of two Elements as identified in the Reliability Standards (for example, loss of two Elements as a result of a breaker failure), lead to a reliability issue on another entity’s system (such as a neighboring entity’s Element exceeding an applicable rating, or loss of non-consequential load due to a single contingency)? Conversely, will such contingencies on a neighboring entity’s system result in issues for Reliability Standards compliance on the system of the entity in question?
3. Can the normal operation, misoperation or malicious use of the entity’s cyber assets cause a detrimental impact (e.g., by limiting the operational alternatives) on the operational reliability of an associated Balancing Authority, Generator Operator or Transmission Operator?
4. Can the normal operation, misoperation, or malicious use of the entity’s Protection Systems (including UFLS, UVLS, Special Protection System, Remedial Action Schemes and other Protection Systems protecting BES Facilities) cause an adverse impact on the operational reliability of any associated Balancing Authority, Generator Operator or Transmission Operator, or the automatic load shedding programs of a PC or TP (UFLS, UVLS)?

## Limitation of responsibilities to a sub-set of Reliability Standards

NERC may limit the compliance obligations of (1) a given entity registered for a particular function or (2) a similarly situated class of entities, as warranted based on the particular facts and circumstances, to a sub-set list of Reliability Standards (which may specify Requirements/sub-Requirements). If NERC establishes a sub-set list for similarly situated class of entities, NERC will post the eligibility criteria and sub-set list of applicable Reliability Standards to the Registration and Certification page of the NERC Website.

---

<sup>9</sup> The Determination of Material Impact applies when an entity seeks a NERC-led Registration Review Panel to review its request for examination of registration based on material impact. As stated in Appendix 5A, “[t]he Panel shall also include a review of individual and aggregate system-wide risks to, and considerations of, reliability of the BPS, as well as the BES Definition, as applicable.” Appendix 5A, Section III(D). Any such request will be reviewed on a case by case basis in accordance with the Panel procedures set forth in Appendix 5A.