

Project 2008-04 — Revisions to FAC-010, FAC-011, and FAC-014

Standard Development Roadmap

This section is maintained by the drafting team during the development of the standard and will be removed when the standard becomes effective.

Development Steps Completed:

SAR posted for comment with draft standard for 45-day comment period from January 21 – March 5, 2008.

Second draft of SAR and proposed changes to standards posted for a 30-day comment period from March 31–April 29, 2008.

Posted for 30-day pre-ballot review from May 2–31, 2008.

Initial ballot conducted from June 2–12, 2008

Proposed Action Plan and Description of Current Draft:

This is the fourth draft of Standard posted for recirculation ballot review.

Future Development Plan:

Anticipated Actions	Anticipated Date
1. Post response to comments on initial ballot.	June 13, 2008
2. Conduct recirculation ballot.	June 13–22, 2008
3. Board adoption.	June 26, 2008
4. Submit to regulatory authorities for approval.	June 30, 2008

Definitions of Terms Used in Standard

This section includes all newly defined or revised terms used in the proposed standard. Terms already defined in the Reliability Standards Glossary of Terms are not repeated here. New or revised definitions listed below become approved when the proposed standard is approved. When the standard becomes effective, these defined terms will be removed from the individual standard and added to the Glossary.

None.

A. Introduction

1. **Title:** System Operating Limits Methodology for the Operations Horizon
2. **Number:** FAC-011-2
3. **Purpose:** To ensure that System Operating Limits (SOLs) used in the reliable operation of the Bulk Electric System (BES) are determined based on an established methodology or methodologies.
4. **Applicability**
 - 4.1. Reliability Coordinator
5. **Effective Date:** October 1, 2008

B. Requirements

- R1. The Reliability Coordinator shall have a documented methodology for use in developing SOLs (SOL Methodology) within its Reliability Coordinator Area. This SOL Methodology shall:
 - R1.1. Be applicable for developing SOLs used in the operations horizon.
 - R1.2. State that SOLs shall not exceed associated Facility Ratings.
 - R1.3. Include a description of how to identify the subset of SOLs that qualify as IROLs.
- R2. The Reliability Coordinator's SOL Methodology shall include a requirement that SOLs provide BES performance consistent with the following:
 - R2.1. In the pre-contingency state, the BES shall demonstrate transient, dynamic and voltage stability; all Facilities shall be within their Facility Ratings and within their thermal, voltage and stability limits. In the determination of SOLs, the BES condition used shall reflect current or expected system conditions and shall reflect changes to system topology such as Facility outages.
 - R2.2. Following the single Contingencies¹ identified in Requirement 2.2.1 through Requirement 2.2.3, the system shall demonstrate transient, dynamic and voltage stability; all Facilities shall be operating within their Facility Ratings and within their thermal, voltage and stability limits; and Cascading or uncontrolled separation shall not occur.
 - R2.2.1. Single line to ground or 3-phase Fault (whichever is more severe), with Normal Clearing, on any Faulted generator, line, transformer, or shunt device.
 - R2.2.2. Loss of any generator, line, transformer, or shunt device without a Fault.
 - R2.2.3. Single pole block, with Normal Clearing, in a monopolar or bipolar high voltage direct current system.
 - R2.3. In determining the system's response to a single Contingency, the following shall be acceptable:

¹ The Contingencies identified in FAC-011 R2.2.1 through R2.2.3 are the minimum contingencies that must be studied but are not necessarily the only Contingencies that should be studied.

- R2.3.1.** Planned or controlled interruption of electric supply to radial customers or some local network customers connected to or supplied by the Faulted Facility or by the affected area.
 - R2.3.2.** Interruption of other network customers, (a) only if the system has already been adjusted, or is being adjusted, following at least one prior outage, or (b) if the real-time operating conditions are more adverse than anticipated in the corresponding studies
 - R2.3.3.** System reconfiguration through manual or automatic control or protection actions.
 - R2.4.** To prepare for the next Contingency, system adjustments may be made, including changes to generation, uses of the transmission system, and the transmission system topology.
- R3.** The Reliability Coordinator’s methodology for determining SOLs, shall include, as a minimum, a description of the following, along with any reliability margins applied for each:
 - R3.1.** Study model (must include at least the entire Reliability Coordinator Area as well as the critical modeling details from other Reliability Coordinator Areas that would impact the Facility or Facilities under study.)
 - R3.2.** Selection of applicable Contingencies
 - R3.3.** A process for determining which of the stability limits associated with the list of multiple contingencies (provided by the Planning Authority in accordance with FAC-014 Requirement 6) are applicable for use in the operating horizon given the actual or expected system conditions.
 - R3.3.1.** This process shall address the need to modify these limits, to modify the list of limits, and to modify the list of associated multiple contingencies.
 - R3.4.** Level of detail of system models used to determine SOLs.
 - R3.5.** Allowed uses of Special Protection Systems or Remedial Action Plans.
 - R3.6.** Anticipated transmission system configuration, generation dispatch and Load level
 - R3.7.** Criteria for determining when violating a SOL qualifies as an Interconnection Reliability Operating Limit (IROL) and criteria for developing any associated IROL T_v.
- R4.** The Reliability Coordinator shall issue its SOL Methodology and any changes to that methodology, prior to the effectiveness of the Methodology or of a change to the Methodology, to all of the following:
 - R4.1.** Each adjacent Reliability Coordinator and each Reliability Coordinator that indicated it has a reliability-related need for the methodology.
 - R4.2.** Each Planning Authority and Transmission Planner that models any portion of the Reliability Coordinator’s Reliability Coordinator Area.
 - R4.3.** Each Transmission Operator that operates in the Reliability Coordinator Area.

- R5.** If a recipient of the SOL Methodology provides documented technical comments on the methodology, the Reliability Coordinator shall provide a documented response to that recipient within 45 calendar days of receipt of those comments. The response shall indicate whether a change will be made to the SOL Methodology and, if no change will be made to that SOL Methodology, the reason why.

C. Measures

- M1.** The Reliability Coordinator's SOL Methodology shall address all of the items listed in Requirement 1 through Requirement 3.
- M2.** The Reliability Coordinator shall have evidence it issued its SOL Methodology, and any changes to that methodology, including the date they were issued, in accordance with Requirement 4.
- M3.** If the recipient of the SOL Methodology provides documented comments on its technical review of that SOL methodology, the Reliability Coordinator that distributed that SOL Methodology shall have evidence that it provided a written response to that commenter within 45 calendar days of receipt of those comments in accordance with Requirement 5

D. Compliance

1. Compliance Monitoring Process

1.1. Compliance Monitoring Responsibility

Regional Reliability Organization

1.2. Compliance Monitoring Period and Reset Time Frame

Each Reliability Coordinator shall self-certify its compliance to the Compliance Monitor at least once every three years. New Reliability Authorities shall demonstrate compliance through an on-site audit conducted by the Compliance Monitor within the first year that it commences operation. The Compliance Monitor shall also conduct an on-site audit once every nine years and an investigation upon complaint to assess performance.

The Performance-Reset Period shall be twelve months from the last non-compliance.

1.3. Data Retention

The Reliability Coordinator shall keep all superseded portions to its SOL Methodology for 12 months beyond the date of the change in that methodology and shall keep all documented comments on its SOL Methodology and associated responses for three years. In addition, entities found non-compliant shall keep information related to the non-compliance until found compliant.

The Compliance Monitor shall keep the last audit and all subsequent compliance records.

1.4. Additional Compliance Information

The Reliability Coordinator shall make the following available for inspection during an on-site audit by the Compliance Monitor or within 15 business days of a request as part of an investigation upon complaint:

1.4.1 SOL Methodology.

- 1.4.2** Documented comments provided by a recipient of the SOL Methodology on its technical review of a SOL Methodology, and the associated responses.
 - 1.4.3** Superseded portions of its SOL Methodology that had been made within the past 12 months.
 - 1.4.4** Evidence that the SOL Methodology and any changes to the methodology that occurred within the past 12 months were issued to all required entities.
- 2.** Levels of Non-Compliance for Western Interconnection: **(To be replaced with VSLs once developed and approved by WECC)**
 - 2.1. Level 1:** There shall be a level one non-compliance if either of the following conditions exists:
 - 2.1.1** The SOL Methodology did not include a statement indicating that Facility Ratings shall not be exceeded.
 - 2.1.2** No evidence of responses to a recipient's comments on the SOL Methodology
 - 2.2. Level 2:** The SOL Methodology did not include a requirement to address all of the elements in R3.1, R3.2, R3.4 through R3.7 and E1.
 - 2.3. Level 3:** There shall be a level three non-compliance if any of the following conditions exists:
 - 2.3.1** The SOL Methodology did not include a statement indicating that Facility Ratings shall not be exceeded and the methodology did not include evaluation of system response to one of the three types of single Contingencies identified in R2.2.
 - 2.3.2** The SOL Methodology did not include a statement indicating that Facility Ratings shall not be exceeded and the methodology did not include evaluation of system response to two of the seven types of multiple Contingencies identified in E1.1.
 - 2.3.3** The System Operating Limits Methodology did not include a statement indicating that Facility Ratings shall not be exceeded and the methodology did not address two of the six required topics in R3.1, R3.2, R3.4 through R3.7.
 - 2.4. Level 4:** The SOL Methodology was not issued to all required entities in accordance with R4.

3. Violation Severity Levels:

Requirement	Lower	Moderate	High	Severe
R1	Not applicable.	The Reliability Coordinator has a documented SOL Methodology for use in developing SOLs within its Reliability Coordinator Area, but it does not address R1.2	The Reliability Coordinator has a documented SOL Methodology for use in developing SOLs within its Reliability Coordinator Area, but it does not address R1.3.	The Reliability Coordinator has a documented SOL Methodology for use in developing SOLs within its Reliability Coordinator Area, but it does not address R1.1. OR The Reliability Coordinator has no documented SOL Methodology for use in developing SOLs within its Reliability Coordinator Area.
R2	The Reliability Coordinator’s SOL Methodology requires that SOLs are set to meet BES performance following single contingencies, but does not require that SOLs are set to meet BES performance in the pre-contingency state. (R2.1)	Not applicable.	The Reliability Coordinator’s SOL Methodology requires that SOLs are set to meet BES performance in the pre-contingency state, but does not require that SOLs are set to meet BES performance following single contingencies. (R2.2 – R2.4)	The Reliability Coordinator’s SOL Methodology does not require that SOLs are set to meet BES performance in the pre-contingency state and does not require that SOLs are set to meet BES performance following single contingencies. (R2.1 through R2.4)
R3	The Reliability Coordinator has a methodology for determining SOLs that includes a description for all but one of the following:	The Reliability Coordinator has a methodology for determining SOLs that includes a description for all but two of the following:	The Reliability Coordinator has a methodology for determining SOLs that includes a description for all but three of the following:	The Reliability Coordinator has a methodology for determining SOLs that is missing a description of three or more of the

Requirement	Lower	Moderate	High	Severe
	R3.1 through R3.7.	R3.1 through R3.7.	R3.1 through R3.7.	following: R3.1 through R3.7.
R4	<p>One or both of the following:</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but one of the required entities.</p> <p>For a change in methodology, the changed methodology was provided up to 30 calendar days after the effectiveness of the change.</p>	<p>One of the following:</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but one of the required entities AND for a change in methodology, the changed methodology was provided 30 calendar days or more, but less than 60 calendar days after the effectiveness of the change.</p> <p>OR</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but two of the required entities AND for a change in methodology, the changed methodology was provided up to 30 calendar days after the effectiveness of the change.</p>	<p>One of the following:</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but one of the required entities AND for a change in methodology, the changed methodology was provided 60 calendar days or more, but less than 90 calendar days after the effectiveness of the change.</p> <p>OR</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but two of the required entities AND for a change in methodology, the changed methodology was provided 30 calendar days or more, but less than 60 calendar days after the effectiveness of the change.</p> <p>OR</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that</p>	<p>One of the following:</p> <p>The Reliability Coordinator failed to issue its SOL Methodology and changes to that methodology to more than three of the required entities.</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but one of the required entities AND for a change in methodology, the changed methodology was provided 90 calendar days or more after the effectiveness of the change.</p> <p>OR</p> <p>The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but two of the required entities AND for a change in methodology, the changed methodology was provided 60 calendar days or more, but less than 90 calendar days after the effectiveness</p>

Requirement	Lower	Moderate	High	Severe
			<p>methodology to all but three of the required entities AND for a change in methodology, the changed methodology was provided up to 30 calendar days after the effectiveness of the change.</p>	<p>of the change. OR The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but three of the required entities AND for a change in methodology, the changed methodology was provided 30 calendar days or more, but less than 60 calendar days after the effectiveness of the change. OR The Reliability Coordinator issued its SOL Methodology and changes to that methodology to all but four of the required entities AND for a change in methodology, the changed methodology was provided up to 30 calendar days after the effectiveness of the change.</p>
R5	The Reliability Coordinator received documented technical comments on its SOL Methodology and provided a complete response in a time period	The Reliability Coordinator received documented technical comments on its SOL Methodology and provided a complete response in a time period	The Reliability Coordinator received documented technical comments on its SOL Methodology and provided a complete response in a time period	The Reliability Coordinator received documented technical comments on its SOL Methodology and provided a complete response in a time period

Requirement	Lower	Moderate	High	Severe
	<p>that was longer than 45 calendar days but less than 60 calendar days.</p>	<p>that was 60 calendar days or longer but less than 75 calendar days.</p>	<p>that was 75 calendar days or longer but less than 90 calendar days.</p> <p>OR</p> <p>The Reliability Coordinator’s response to documented technical comments on its SOL Methodology indicated that a change will not be made, but did not include an explanation of why the change will not be made.</p>	<p>that was 90 calendar days or longer.</p> <p>OR</p> <p>The Reliability Coordinator’s response to documented technical comments on its SOL Methodology did not indicate whether a change will be made to the SOL Methodology.</p>

Regional Differences

1. The following Interconnection-wide Regional Difference shall be applicable in the Western Interconnection:
 - 1.1. As governed by the requirements of R3.3, starting with all Facilities in service, shall require the evaluation of the following multiple Facility Contingencies when establishing SOLs:
 - 1.1.1 Simultaneous permanent phase to ground Faults on different phases of each of two adjacent transmission circuits on a multiple circuit tower, with Normal Clearing. If multiple circuit towers are used only for station entrance and exit purposes, and if they do not exceed five towers at each station, then this condition is an acceptable risk and therefore can be excluded.
 - 1.1.2 A permanent phase to ground Fault on any generator, transmission circuit, transformer, or bus section with Delayed Fault Clearing except for bus sectionalizing breakers or bus-tie breakers addressed in E1.1.7
 - 1.1.3 Simultaneous permanent loss of both poles of a direct current bipolar Facility without an alternating current Fault.
 - 1.1.4 The failure of a circuit breaker associated with a Special Protection System to operate when required following: the loss of any element without a Fault; or a permanent phase to ground Fault, with Normal Clearing, on any transmission circuit, transformer or bus section.
 - 1.1.5 A non-three phase Fault with Normal Clearing on common mode Contingency of two adjacent circuits on separate towers unless the event frequency is determined to be less than one in thirty years.
 - 1.1.6 A common mode outage of two generating units connected to the same switchyard, not otherwise addressed by FAC-011.
 - 1.1.7 The loss of multiple bus sections as a result of failure or delayed clearing of a bus tie or bus sectionalizing breaker to clear a permanent Phase to Ground Fault.
 - 1.2. SOLs shall be established such that for multiple Facility Contingencies in E1.1.1 through E1.1.5 operation within the SOL shall provide system performance consistent with the following:
 - 1.2.1 All Facilities are operating within their applicable Post-Contingency thermal, frequency and voltage limits.
 - 1.2.2 Cascading does not occur.
 - 1.2.3 Uncontrolled separation of the system does not occur.
 - 1.2.4 The system demonstrates transient, dynamic and voltage stability.
 - 1.2.5 Depending on system design and expected system impacts, the controlled interruption of electric supply to customers (load shedding), the planned

removal from service of certain generators, and/or the curtailment of contracted firm (non-recallable reserved) electric power transfers may be necessary to maintain the overall security of the interconnected transmission systems.

1.2.6 Interruption of firm transfer, Load or system reconfiguration is permitted through manual or automatic control or protection actions.

1.2.7 To prepare for the next Contingency, system adjustments are permitted, including changes to generation, Load and the transmission system topology when determining limits.

1.3. SOLs shall be established such that for multiple Facility Contingencies in E1.1.6 through E1.1.7 operation within the SOL shall provide system performance consistent with the following with respect to impacts on other systems:

1.3.1 Cascading does not occur.

1.4. The Western Interconnection may make changes (performance category adjustments) to the Contingencies required to be studied and/or the required responses to Contingencies for specific facilities based on actual system performance and robust design. Such changes will apply in determining SOLs.

Version History

Version	Date	Action	Change Tracking
1	November 1, 2006	Adopted by Board of Trustees	New
2		Changed the effective date to October 1, 2008 Changed “Cascading Outage” to “Cascading” Replaced Levels of Non-compliance with Violation Severity Levels Corrected footnote 1 to reference FAC-011 rather than FAC-010	Revised